







Smart Chime

Wireless chime that can be plugged into a standard wall outlet and used with UniFi Protect doorbells.

The Smart Chime (UP Chime) is a wireless, mesh-covered chime that pairs with a UniFi Protect doorbell and rings whenever it is pressed. This peripheral device is ideal for households that do not have a wired chime system or have one that is incompatible with their Protect doorbell. The Smart Chime is also seamlessly integrated with UniFi Protect to ensure that it's simple to set up and manage via either the web application or mobile app.



Dimensions	UP-Chime-US: \emptyset 62 x 50.6 mm (\emptyset 2.44 x 1.99") (without prong) UP-Chime-EU: \emptyset 62 x 68.93 mm (\emptyset 2.44 x 2.71") (without prong)
Weight	UP-Chime-US: 127 g (4.48 oz) UP-Chime-EU: 135 g (4.76 oz)
Enclosure materials	Polycarbonate, fabric

System

Processor	Single/Dual-Core® Xtensa® 32 bit 400MIPS
Memory	520 kB SRAM 448 kB ROM
Management application	UniFi Protect
Networking interface	WiFi 802.11 b/g/n
Button	Factory reset
LEDs	(5) White
Power method	AC
Supported voltage range	100-240V, 50-60 Hz
Max. power consumption	3.7W
Antenna gain	2 dBi
ESD/EMP protection	Air: ± 16kV, contact: ± 8kV
Operating temperature	0 to 40° C (32 to 104° F)
Operating humidity	10 to 90% noncondensing
Certifications	FCC, IC, CE

Audio

Speaker	Yes
Buzzer	Yes

Software

UniFi OS application	UniFi Protect
Mobile apps	UniFi Protect (iOS and Android)

